

GenX Board Installation Guide for Arduino:

In order to upload Marlin code onto GenX board, the user must import the GenX folder into the Arduino IDE folder.

Make sure you have closed your Arduino software first. Then locate the Arduino IDE directory on your system. Look for “hardware” folder within the main Arduino IDE folder. Once you found it copy the supplied GenX folder inside the “hardware” folder. The next time you run the Arduino software choose GenX as your selected board from the Tools > Board menu (Tools>Boards>GenX). Now you are set to upload Marlin code onto your GenX board through a valid serial port.